

# Kernel

[The Linux kernel user's and administrator's guide](#)

## Info

- query CPU information: `cpuid`
- show system/kernel info: `uname -a`
- show (or configure) kernel parameters at runtime: `sysctl -a`
- show kernel memory usage: `free`
- show modules loaded: `lsmod`
- show all module parameters: `modinfo -p <modname>`
- show current module parameters: `systool -m <modname> -av`

## Logs

- show kernel (boot) messages: `dmesg`
- configure to show more kernel messages (with timestamp)

```
echo 8 > /proc/sys/kernel/printk
echo Y > /sys/module/printk/parameters/time
```

or use for example `loglevel=7` as kernel boot parameter (as recommended at [StackOverflow](#)).

## Udev

### Links

- Ubuntuusers Wiki: [udev](#)
- ArchWiki: [udev](#)
- Daniel Drake: [Writing udev rules](#)
- Stack Exchange: [Automount USB sticks on Gentoo](#)

### Commands

- show *udev* daemon<sup>1)</sup> events: `udevadm monitor --environment`
- after changing *udev* rules: `udevadm control --reload`

### Files

- `/etc/udev/rules.d, /lib/udev/rules.d`: *udev* rules

## Block Devices

- show all block devices: `lsblk`
- show hard drive information: `hdparm -I /dev/sda`
- blacklist the UAS driver for LaCie USB mass storage in file `/etc/modprobe.d/usb-storage-quirks.conf`:<sup>2)</sup>

```
# Do not use USB driver UAS (USB Attached SCSI) with LaCie mass
storage.
# This is a younger USB 3.x protocol and not stable at the moment.
# See usb-storage.quirks in
https://www.kernel.org/doc/Documentation/admin-guide/kernel-parameters.
txt
options usb-storage quirks=059f:105e:u
```

## Hardware

### Links

- Super User: [What is the Linux command to find out hardware info?](#)
- Pratham Patel: [Get All Kind of System Information in Linux Terminal With inxi](#)

### PCI

- show PCI information: `lspci -k -nn`

### USB

- show tree of USB devices: `lsusb -t`

### Bluetooth

#### Links

- ArchWiki: [Bluetooth](#)
- ArchWiki: [Bluetooth keyboard](#)
- ArchWiki: [Bluetooth mouse](#)
- ArchWiki: [Bluetooth - Pairing](#)
- BITblokes (JDO): [MX Keys Mini \(Logitech\) mit Linux verbinden – gute Tastatur, ABER](#)

## Troubleshooting

### Checklist:

1. check kernel module *btusb* is load and running: `lsmod | grep btusb`
2. check for kernel problems: `dmesg | grep -i bluetooth`
3. check *Bluetooth* status: `sudo systemctl status bluetooth`, or `sudo service bluetooth status`
4. after changing files in `/etc/bluetooth` do: `sudo service bluetooth restart`
5. use `sudo bluetoothctl` to check for *Bluetooth* devices and their state (also the *Blueman* applet might be useful for this)
6. check [Laptop Power Management](#) for *Bluetooth* status: `sudo tlp-stat -u -v`
7. change `/etc/default/tlp` to adjust *Laptop Power Management* regarding *Bluetooth*:
  - [TLP Settings](#)
  - [TLP FAQ](#)

1)

User space device manager for `/dev`.

2)

See also StackExchange: [Connection problem with USB3 external storage on Linux \(UAS driver problem\)](#).

From:

<https://wiki.rho62.de/> - **rho62 Wiki**

Permanent link:

<https://wiki.rho62.de/doku.php?id=linux:administration:kernel>

Last update: **2024/11/07 13:21**

